



ELECTRICAL DESIGN GROUP

ELECTRICAL BUILDING SERVICES CONSULTANTS

P.O. Box 15, SHERWOOD Q. 4075

Phone: (07) 3278 4375 Fax: (07) 3716 0222

Web Site: www.edg.net.au Email: brisbane@edg.net.au


C3648a - KALLANGUR TAVERN

C3648a-0004(A).xls

LIGHTING CONTROL SCHEDULE

REVISION A - 29 OCTOBER 2025

MISCELLANEOUS EQUIPMENT					REV
ITEM	DESCRIPTION				A
SP1	AS DETAILED IN THE EQUIPMENT SCHEDULE 6-BUTTON PROGRAMMABLE SWITCH PANEL C/W CENTRAL LCD DISPLAY DYNALITE ANTUMBRA DISPLAY ALUMINIUM				A
SP2	AS DETAILED IN THE EQUIPMENT SCHEDULE 6-BUTTON PROGRAMMABLE SWITCH PANEL C/W CENTRAL LCD DISPLAY DYNALITE ANTUMBRA DISPLAY ALUMINIUM				A
SP3	AS DETAILED IN THE EQUIPMENT SCHEDULE 6-BUTTON PROGRAMMABLE SWITCH PANEL C/W CENTRAL LCD DISPLAY DYNALITE ANTUMBRA DISPLAY ALUMINIUM				A
SP4	AS DETAILED IN THE EQUIPMENT SCHEDULE 6-BUTTON PROGRAMMABLE SWITCH PANEL C/W CENTRAL LCD DISPLAY DYNALITE ANTUMBRA DISPLAY ALUMINIUM				A
PE CELL	PROGRAMMABLE PE CELL DUS 90CS CONFIRM THE LOCATION ON SITE WITH THE ARCHITECT				A
TIME CLOCK	PROGRAMMABLE TIME CLOCK ENVISION GATEWAY PDEG LOCATED IN DB-A				A
CONTROL MODULE 1					A
TYPE:		DYNALITE DDRC1220FR-GL			A
DESCRIPTION		12CH 20 A FEEDTHROUGH RELAY CONTROLLER			A
LOCATION		DIN RAIL MOUNTED WITHIN DB-L			A
BUS:		A			A
CHANNEL	CONTROL	DESCRIPTION			A
		LOCATION	CIRCUIT	USE	A
1	SWITCHED	EXTERNAL	DB-L- L1	SIGN	A
2	SWITCHED	EXTERNAL	DB-L- L2	SIGN	A
3	SWITCHED	EXTERNAL	DB-L- L3	SIGN	A
4	SWITCHED	GAMING	2CHANNEL CONTACTOR	G1	A
5	SWITCHED	GAMING	4CHANNEL CONTACTOR	SIGNAGE	A
6					A
7					A
8					A
9					A
10					A
11					A
12					A
CONTROL MODULE 2					A
TYPE:		DYNALITE DDBC1200			A
DESCRIPTION		12CH BOARD CAST DALI CONTROLLER			A
LOCATION		DIN RAIL MOUNTED WITHIN DB-L			A
BUS:		A			A
CHANNEL	CONTROL	DESCRIPTION			A
		LOCATION	CIRCUITS	USE	A
13	DALI DIM	GAMING AMENITY	DB-L- L4	L1 VIA A DALI TO TE CONVERTER	A
14	DALI DIM	GAMING	DB-L- L4	L1 VIA A DALI TO TE CONVERTER	A
15	DALI DIM	ENTRY	DB-L- L4	L1 VIA A DALI TO TE CONVERTER	A
16	DALI DIM	ENTRY	DB-L- L4	L1 VIA A DALI TO TE CONVERTER	A
17	DALI DIM	GAMING	DB-L- L4	S4	A
18	DALI DIM	GAMING	DB-L- L4	L8	A
19	DALI DIM	GAMING	DB-L- L5	L8	A
20	DALI DIM	GAMING BAR	DB-L- L6	S1	A
21	DALI DIM	GAMING BAR	DB-L- L6	S2	A
22	DALI DIM	GAMING	DB-L- L6	S10	A
23	DALI DIM	GAMING BAR	DB-L- L6	S3	A
24					A



ELECTRICAL DESIGN GROUP

ELECTRICAL BUILDING SERVICES CONSULTANTS

P.O. Box 15, SHERWOOD Q. 4075

Phone: (07) 3278 4375 Fax: (07) 3716 0222

Web Site: www.edg.net.au Email: brisbane@edg.net.au


C3648a - KALLANGUR TAVERN

C3648a-0004(A).xls

LIGHTING CONTROL SCHEDULE

REVISION A - 29 OCTOBER 2025

CONTROL MODULE 3					A
TYPE:		DYNALITE DDBC1200			A
DESCRIPTION		12CH BOARD CAST DALI CONTROLLER			A
LOCATION		DIN RAIL MOUNTED WITHIN DB-L			A
BUS:		A			A
CHANNEL	CONTROL	DESCRIPTION			A
		LOCATION	CIRCUITS	USE	A
25	DALI DIM	GAMING AMENITY	DB-L- L7	L10	A
26	DALI DIM	GAMING AMENITY	DB-L- L7	L15	A
27	DALI DIM	GAMING DOSA	DB-L- L7	L10	A
28	DALI DIM	GAMING	DB-L- L8	S7	A
29	DALI DIM	GAMING	DB-L- L8	L2 VIA A DALI TO TE CONVERTER	A
30	DALI DIM	GAMING	DB-L- L9	L18	A
31	DALI DIM	GAMING BAR	DB-L- L10	L17	A
32	DALI DIM	GAMING BAR	DB-L- L10	L16	A
33	DALI DIM	ENTRY	DB-L- L10	L15	A
34	DALI DIM	ENTRY	DB-L- L10	L15	A
35					A
36					A
CONTROL MODULE 4					A
TYPE:		DYNALITE DDBC1200			A
DESCRIPTION		12CH BOARD CAST DALI CONTROLLER			A
LOCATION		DIN RAIL MOUNTED WITHIN DB-L			A
BUS:		A			A
CHANNEL	CONTROL	DESCRIPTION			A
		LOCATION	CIRCUITS	USE	A
37	DALI DIM	ENTRY	DB-L- L11	L10	A
38	DALI DIM	ENTRY	DB-L- L11	L20	A
39	DALI DIM	ENTRY	DB-L- L11	S9	A
40	DALI DIM	ENTRY	DB-L- L11	S6	A
41	DALI DIM	ENTRY	DB-L- L11	S6	A
42	DALI DIM	ENTRY	DB-L- L11	L2 VIA A DALI TO TE CONVERTER	A
43	DALI DIM	BISTRO	DB-L- L12	L10	A
44	DALI DIM	BISTRO	DB-L- L12	L15	A
45	DALI DIM	BISTRO	DB-L- L12	L15	A
46	DALI DIM	BISTRO	DB-L- L13	L4 VIA A DALI TO TE CONVERTER	A
47	DALI DIM	BISTRO	DB-L- L13	L4 VIA A DALI TO TE CONVERTER	A
48	DALI DIM	BISTRO	DB-L- L14	L4 VIA A DALI TO TE CONVERTER	A
CONTROL MODULE 5 SL01					A
TYPE:		DYNALITE DDBC1200			A
DESCRIPTION		12CH BOARD CAST DALI CONTROLLER			A
LOCATION		DIN RAIL MOUNTED WITHIN DB-L			A
BUS:		A			A
CHANNEL	CONTROL	DESCRIPTION			A
		LOCATION	CIRCUITS	USE	A
49	DALI DIM	BISTRO	DB-L- L15	L17	A
50	DALI DIM	BISTRO	DB-L- L15	S3	A
51	DALI DIM	BISTRO	DB-L- L15	L16	A
52	DALI DIM	BISTRO	DB-L- L15	S8	A
53	DALI DIM	EXTERNAL	DB-L- L16	L20	A
54	DALI DIM	EXTERNAL	DB-L- L16	L10	A
55	DALI DIM	EXTERNAL	DB-L- L16	L20	A
56	DALI DIM	KIDS	DB-L- L16	L10	A
57	DALI DIM	KIDS	DB-L- L16	L10	A
58	DALI DIM	KIDS	DB-L- L17	L10	A
59	DALI DIM	BISTRO AMENITY	DB-L- L17	L10	A
60	DALI DIM	BISTRO AMENITY	DB-L- L17	L19 VIA A DALI TO TE CONVERTER	A



ELECTRICAL DESIGN GROUP

ELECTRICAL BUILDING SERVICES CONSULTANTS

P.O. Box 15, SHERWOOD Q. 4075

Phone: (07) 3278 4375 Fax: (07) 3716 0222

Web Site: www.edg.net.au Email: brisbane@edg.net.au

C3648a - KALLANGUR TAVERN

C3648a-0004(A).xls

LIGHTING CONTROL SCHEDULE

REVISION A - 29 OCTOBER 2025

CONTROL MODULE 6					A
TYPE:		DYNALITE DDBC1200			A
DESCRIPTION		12CH BOARD CAST DALI CONTROLLER			A
LOCATION		DIN RAIL MOUNTED WITHIN DB-L			A
BUS:		A			A
CHANNEL	CONTROL	DESCRIPTION			A
		LOCATION	CIRCUITS	USE	A
61	DALI DIM	SPORTS BAR	DB-L- L18	L14	A
62	DALI DIM	SPORTS BAR	DB-L- L18	L14	A
63	DALI DIM	SPORTS BAR	DB-L- L18	S5	A
64	DALI DIM	SPORTS BAR	DB-L- L19	L15	A
65	DALI DIM	SPORTS BAR	DB-L- L19	S5	A
66	DALI DIM	SPORTS BAR	DB-L- L19	L14	A
67	DALI DIM	EXTERNAL	DB-L- L20	L7 VIA A DALI TO TE CONVERTER	A
68	DALI DIM	SPORTS BAR AMENITY	DB-L- L20	L10	A
69	DALI DIM	SPORTS BAR	DB-L- L21	L10	A
70	DALI DIM	SPORTS BAR	DB-L- L21	L10	A
71	DALI DIM	SPORTS BAR	DB-L- L22	L10	A
72	DALI DIM	SPORTS BAR AMENITY	DB-L- L22	L11 VIA A DALI TO TE CONVERTER	A
CONTROL MODULE 7					A
TYPE:		DYNALITE DDBC1200			A
DESCRIPTION		12CH BOARD CAST DALI CONTROLLER			A
LOCATION		DIN RAIL MOUNTED WITHIN DB-L			A
BUS:		A			A
CHANNEL	CONTROL	DESCRIPTION			A
		LOCATION	CIRCUITS	USE	A
73	DALI DIM	SPORTS BAR	DB-L- L23	S1	A
74	DALI DIM	SPORTS BAR	DB-L- L23	S1	A
75	DALI DIM	SPORTS BAR	DB-L- L23	S4	A
76	DALI DIM		DB-L- L23	L6	A
77	DALI DIM	EXTERNAL	DB-L- L23	L9	A
78	DALI DIM	BISTRO	DB-L- L24	L3 VIA A DALI TO TE CONVERTER	A
79	DALI DIM	BISTRO	DB-L- L24	S4	A
80	DALI DIM	BISTRO BAR	DB-L- L24	S2	A
81	DALI DIM	BISTRO BAR	DB-L- L24	S1	A
82	DALI DIM	EXTERNAL	DB-L- L25	L5 VIA A DALI TO TE CONVERTER	A
83	DALI DIM	EXTERNAL	DB-L- L25	L9	A
84	DALI DIM	EXTERNAL	DB-L- L25	B1	A