ELECTRICAL DESIGN GROUP



C2559a-0011(B).xls

А

C2559a - THE BELVEDERE HOTEL, WOODY POINT DISTRIBUTION BOARD DB-C (LEVEL 1 NORTH) REVISION B - 30 JUNE 2022

				REV		
FAULT CURRENT:	6KA USING CASCADING	MAIN SWITCH:	250A NON AUTO LOAD BREAK	А		
CHASSIS SIZE:	60 POLES	SUPPLIED FROM:	MSB	А		
CHASSIS RATING:	250A	SUPPLY CABLE:	4C70	А		
PHASES:	3			А		
PROVIDE THE DB WITH A FULL WIDTH EMPTY DIN RAIL TO ACCOMMODATE FUTURE CONTACTORS AND CONTROLS IN ADDITION TO						

PROVIDE THE DB WITH A FULL WIDTH EMPTY DIN RAIL TO ACCOMMODATE FUTURE CONTACTORS AND CONTROLS IN ADDITION TO THE INITIAL PHILIPS DYNALITE CONTROLS .. DB-A IS INTEGRAL TO THE MSB REFER TO THE POWER SCHEMATIC. REINSTATE THE EXISTING MSB SERVICES THAT REMAIN WITH NEW SWITCHGEAR AND CONTROLS TO MATCH THE EXISTING IN CAPACITY AND FUNCTION.

CIRC PH CIRCUIT BREAKER (amps)	CONTROL CABLE	CABLE		CIRCUIT		
	EQUIPMENT	SIZE (mm ²)	LOCATION	USE		
P1 1	20	RCD	2.5	BACK OF HOUSE	CLEANING	A
P2 1	20	RCD	2.5	VERANDA	CLEANING	A
P3 1	20	RCD	2.5	FUNCTION ROOM	GPOs	A
P4 1	20	RCD	2.5	VERANDA	TVS	A
P5 1	20	RCD	2.5	LOUNGE	TVS	A
P6 1	20	RCD	2.5	LOUNGE	CLEANING	A
P7 1	20	RCD	2.5	WASH UP	ICE MACHINE	A
P8 1	20	RCD	2.5	WASH UP	GLASS WASHER	A
P9 1	20	RCD	2.5	WASH UP	GLASS WASHER	A
P10 1	20	RCD	2.5	BAR	REF	A
P11 1	20	RCD	2.5	BAR	GPOs	A
P12 1	20	RCD	2.5	BAR	POS	A
P13						В
P14 1	20	RCD	2.5	BAR	REF	A
P15 1	20	RCD	2.5	BAR	GLASS WASHER	A
P16 1	20	RCD	2.5	BAR	GPOs	A
P17 1	20	RCD	2.5	BAR	GPOs	A
P18 3	20	RCD	2.5	BAR	HWS	В
L1 1	20	RCD	2.5	LEVEL 1 NORTH	HEATER	A
L2 1	20	RCD	2.5	LEVEL 1 NORTH	HEATER	A
L3 1	20	RCD	2.5	LEVEL 1 NORTH	HEATER	A
L4 1	20	RCD	2.5	LEVEL 1 NORTH	HEATER	A
L5 1	20	RCD	2.5	LEVEL 1 NORTH	HEATER	A
L6 1	20	RCD	2.5	LEVEL 1 NORTH	LIGHTS	A
L7 1	20	RCD	2.5	LEVEL 1 NORTH	FANS	A
L8 1	20	RCD	2.5	LEVEL 1 NORTH	LIGHTS	A
L9 1	20	RCD	2.5	LEVEL 1 NORTH	LIGHTS	A
L10 1	20	RCD	2.5	LEVEL 1 NORTH	LIGHTS	A
L11 1	20	RCD	2.5	LEVEL 1 NORTH	LIGHTS	A
L12 1	20	RCD	2.5	LEVEL 1 NORTH	LIGHTS	A
L13 1	20	RCD	2.5	LEVEL 1 NORTH	LIGHTS	A
L14 1	20	RCD	2.5	LEVEL 1 NORTH	LIGHTS	A
-			2.5 2.5			

Pages inc. any attach. 1 of 1