

ELECTRICAL DESIGN GROUP

ELECTRICAL BUILDING SERVICES CONSULTANTS P.O. Box 15, SHERWOOD Q. 4075

Phone: (07) 3278 4375

Website: www.edg.net.au Email: brisbane@edg.net.au

${\tt C3379a-THE\;LION\;RICHLANDS-CARPARK\;UPGRADE\;DISTRIBUTION\;BOARD\;DB-T\;(TANK\;ROOM)}$

C3379a-0005(B).xls

REVISION B - 20 JUNE 2025

							REV			
FAULT CURRENT:			6KA USING CASCADING		MAIN SWITCH:	250A NON AUTO LOAD BREAK	А			
CHASSIS SIZE:			60 POLES		SUPPLIED FROM:	MDB-1	Α			
		CHASSIS RATING:	250A		SUPPLY CABLE:	4C70	Α			
		PHASES:	3				Α			
PROVIDE THE DB WITH A FULL WIDTH EMPTY DIN RAIL TO ACCOMMODATE FUTURE CONTACTORS AND CONTROLS. PROVIDE THE DB WITH AN AS2293 EMERGENCY LIGHTING CONTROL SYSTEM TO CONTROL THE ASSOCIATED EMERGENCY LIGHTS. PROVIDE THE DB WITH SURGE PROTECTION. REFER TO THE NOTES FOR ADDITIONAL REQUIREMENTS										
CIRC	PH	CIRCUIT	CONTROL	CABLE	LOCATION	CIRCUIT				
CIRC		BREAKER (amps)	EQUIPMENT	SIZE (mm ²)		USE				
D1	1	20	PCPO.	2.5	TANK POOM	CP T	Λ			

CIRC	РН	CIRCUIT	CONTROL	CABLE	LOCATION	CIRCUIT	
		BREAKER (amps)	EQUIPMENT	SIZE (mm²)		USE	
P1	1	20	RCBO	2.5	TANK ROOM	CR-T	Α
P2	3	40		6.0	TANK ROOM	MSSB-T	Α
P3	3	20	RCBO	2.5	TANK ROOM	STORM WATER	Α
P4	1	20	RCBO	2.5	TANK ROOM	GPO	Α
P5	1	20	RCBO	2.5	TANK ROOM	HYD PUMP 1	Α
P6	1	20	RCBO	2.5	TANK ROOM	HYD PUMP 2	Α
P7	3	20	RCBO	2.5	TANK ROOM	HYD JACK 1	Α
P8	3	20	RCBO	2.5	TANK ROOM	HYD JACK 2	Α
P9	1	20	RCBO	2.5	TANK ROOM	SPK PUMP 1	Α
P10	1						В
P11	3	20	RCBO	2.5	TANK ROOM	SPK JACK 1	Α
P12							В
L1	1	20	RCBO	2.5	TANK ROOM	LIGHTS	Α
			RCBO PE ON DUSK				
L2	1	20	OFF DAWN	2.5	CARPARK	SHADE SALES	А
L3	1	20	RCBO PE ON DUSK OFF DAWN	2.5	CARPARK	POLE LIGHTS	Α
			OH BAWA				
L4	1	20	RCBO PE ON DUSK	2.5	CARPARK	POLE LIGHTS	Α
			OFF DAWN				
L5	1	20	RCBO PE ON DUSK OFF DAWN	2.5	CARPARK	POLE LIGHTS	Α
L6	1	20	RCBO PE ON DUSK OFF DAWN	2.5	CARPARK	POLE LIGHTS	Α
			RCBO PE ON DUSK				
L7	1	20	OFF DAWN	2.5	CARPARK	GARDEN LIGHTS	Α
L8	1	20	RCBO PE ON DUSK	2.5	CARPARK	GARDEN LIGHTS	Α
			OFF DAWN				igwdap

C3379a-0005(B).xls Pages inc. any attach. 1 of 1