



ELECTRICAL DESIGN GROUP

ELECTRICAL BUILDING SERVICES CONSULTANTS

P.O. Box 15, SHERWOOD Q. 4075

Phone: (07) 3278 4375

Website: www.edg.net.au Email: brisbane@edg.net.au

C3457a - THE LION RICHLANDS - STAGE 2

C3457a-0011(B).xls

DISTRIBUTION BOARD DB-K

REVISION B - 17 JULY 2026

							REV
PROVIDE THE FOLLOWING ADDITIONAL SWITCHGEAR WITHIN THE EXISTING DB-K. THE SWITCHGEAR TYPE IS TO MATCH THE EXISTING USED IN DB-K. ALL SWITCHGEAR MADE SPARE OR REDUNDANT IS TO BE REMOVED. IT IS ACCEPTABLE TO REUSE EXISTING SPARE SWITCHGEAR IF IT IS IN GOOD CONDITION HAS THE CORRECT RATING AND FUNCTIONS.							A
CIRC	PH	CIRCUIT BREAKER (amps)	CONTROL EQUIPMENT	CABLE SIZE (mm ²)	LOCATION	CIRCUIT USE	
P1	3	32	RCBO	6.0	KITCHEN	DISH WASHER	A
P2	1	20	RCBO	2.5	KITCHEN	HEAT LAMPS	A
P3	1	20	RCBO	2.5	KITCHEN	REF	A
P4	3	20	RCBO	2.5	KITCHEN	11KW COMBIE	A
P5	3	20	RCBO	2.5	KITCHEN	11KW COMBIE	A
P6	1	20	RCBO	2.5	KITCHEN	WOK	A
P7	1	20	RCBO	2.5	KITCHEN	RICE COOKER	A
P8	1	20	RCBO	2.5	KITCHEN	MW	A
P9	1	20	RCBO	2.5	KITCHEN	REF	A
P10	1	20	RCBO	2.5	KITCHEN	REF	A
P11	1	20	RCBO	2.5	KITCHEN	SPARE	A
P12	1	20	RCBO	2.5	KITCHEN	SANDWICH PRESS	A
P13	1	20	RCBO	2.5	KITCHEN	TOASTER	A
P14	1	20	RCBO	2.5	KITCHEN	SALAD CHILLER	A
P15	1	20	RCBO	2.5	KITCHEN	PRINTER	A
P16	1	20	RCBO	2.5	KITCHEN	SOUS VIDE	A
P17	1	20	RCBO	2.5	KITCHEN	MW	A
P18	3	20	RCBO	2.5	KITCHEN	11KW COMBIE	A
P19	3	20	RCBO	2.5	KITCHEN	11KW COMBIE	A
P20	1	20	RCBO	2.5	KITCHEN	ICE MACHINE	A
P21	1	20	RCBO	2.5	KITCHEN	REF	A
P22	1	20	RCBO	2.5	KITCHEN	GPOS	A
L1	1	20	RCBO	2.5	KITCHEN	LIGHTING	B